


www.pfcstore.com - 763-425-7890 / 800-328-2350



## GRUNDFOS CUE VARIABLE FREQUENCY DRIVE 40HP - NEMA 12

Horse Power 40 | Full Load Amps  
61 | Enclosure IP55 = NEMA 12 |  
Input Volts 380-500

**Typical Delivery is 2 to 4 weeks**



---

**SKU:** 99616811

**Stock:** Out of stock contact us for  
lead time

**Categories:** [Grundfos CUE VFDs](#)

**Tags:** [GRUNDFOS CUE VFD](#)

**Model Number** CUE 3X380-500V  
IP55 30KW DC

**Part Number** 99616811

## PRODUCT DESCRIPTION

Grundfos CUE VFD is a complete range of external frequency converters designed for speed control of a wide range of Grundfos pumps. CUE has a built-in PI controller and offers the same functionality and user-interface as Grundfos E-pumps. CUE solutions can thus be seen as an extension to the E-pump

[www.pfcstore.com](http://www.pfcstore.com) - 763-425-7890 / 800-328-2350

range.

CUE VFD-solution, you will get the following benefits:

- Grundfos E-pump functionality and user-interface
  - application- and pump-family-related functions
  - increased comfort compared to fixed-speed pumps
  - very easy installation and commissioning compared to standard frequency converters
  - speed control of pumps up to 250 kW
  - speed control of pumps installed in potentially explosive environments.
- CUE offers the following inputs and output:
- RS-485 GENIbus
  - an analog 0-10 V input for external setpoint
  - an analog 0/4-20 mA input for sensor
  - four digital inputs for various functions, for instance external start/stop
  - two signal relays (C/NO/NC).

**Estimated delivery is 3 to 4 weeks**

Product photo could vary from the actual product

[Specs](#)

[Product Guide](#)

[Manual](#)

[Quick Guide Start Up](#)

## ADDITIONAL INFORMATION

|                       |                                |
|-----------------------|--------------------------------|
| <b>Weight</b>         | 60 lbs                         |
| <b>Dimensions</b>     | 30 × 18 × 18 in                |
| <b>Enclosure Type</b> | <a href="#">IP55 = NEMA 12</a> |
| <b>Full Load Amps</b> | <a href="#">61</a>             |

**www.pfcestore.com - 763-425-7890 / 800-328-2350**

**Input Volts**                      380-500